



2019 TIMING AND POST SETTINGS CHART

2019 MODEL	TIMING MARK	DRAW INCHES	LETOFF	MOD LETTER	1 Draw • Set	2 Draw • Set	3 Draw • Set	4 Draw • Set	5 Draw • Set	6 Draw • Set	7 Draw • Set	8 Draw • Set	9 Draw • Set	10 Draw • Set	11 Draw • Set	12 Draw • Set	13 Draw • Set
RECKONING	Cable centered between timing dots	26-31"	80%	19T	31 • 1	30.5 • 2	30 • 3	29.5 • 4	29 • 5	28.5 • 6	28 • 7	27.5 • 8	27 • 9	26.5 • 10	26 • 11		
REALM SR6 **	Cable centered between timing dots	25.5-30"	86%	BT-S	30	29.5	29	28.5	28	27.5	27	26.5	26	25.5			
REALM SS **	Cable centered between timing dots	25-31"	86%	BT-S	31	30.5	30	29.5	29	28.5	28	27.5	27	26.5	26	25.5	25
REALM	Cable centered between timing dots	25-31"	80%	BT-S	31 • 1	30.5 • 2	30 • 3	29.5 • 4	29 • 5	28.5 • 6	28 • 7	27.5 • 8	27 • 9	26.5 • 10	26 • 11	25.5 • 12	25 • 13
REALM X	Cable centered between timing dots	25-31"	80%	BT-S	31 • 1	30.5 • 2	30 • 3	29.5 • 4	29 • 5	28.5 • 6	28 • 7	27.5 • 8	27 • 9	26.5 • 10	26 • 11	25.5 • 12	25 • 13
BT-MAG X	Cable centered between timing dots	29-34"	75-85%	M34	34 • 1	33.5 • 2	33 • 3	32.5 • 4	32 • 5	31.5 • 6	31 • 7	30.5 • 8	30 • 9	29.5 • 10	29 • 11		
BT-MAG	Cable centered between timing dots	26.5-30"	80%	M30	30 • 1	29.5 • 2	29 • 3	28.5 • 4	28 • 5	27.5 • 6	27 • 7	26.5 • 8					
FANATIC 3.0 32" Cam	Cable centered between timing dots	28.5-32.5"	80%	FN80	32.5 • 1	32 • 2	31.5 • 3	31 • 4	30.5 • 5	30 • 6	29.5 • 7	29 • 8	28.5 • 9				
FANATIC 3.0 32" Cam	Cable centered between timing dots	28.5-32.5"	65%	FN65	33 • 1	32.5 • 2	32 • 3	31.5 • 4	31 • 5	30.5 • 6	30 • 7	29.5 • 8	29 • 9				
FANATIC 3.0 29" Cam	Cable centered between timing dots	24-29"	80%	FN80	29 • 1	28.5 • 2	28 • 3	27.5 • 4	27 • 5	26.5 • 6	26 • 7	25.5 • 8	25 • 9	24.5 • 10	24 • 11		
FANATIC 3.0 29" Cam	Cable centered between timing dots	24-29"	65%	FN65	29.5 • 1	29 • 2	28.5 • 3	28 • 4	27.5 • 5	27 • 6	26.5 • 7	26 • 8	25.5 • 9	25 • 10	24.5 • 11		
EVA SHOCKEY SS	Cable centered between timing dots	23.5-28.5"	80%*	ODW	28.5 • 1	28 • 2	27.5 • 3	27 • 4	26.5 • 5	26 • 6	25.5 • 7	25 • 8	24.5 • 9	24 • 10	23.5 • 11		
CARBON ICON	Cable centered between timing dots	26.5-30"	80%†	VP	30 • 1	29.5 • 2	29 • 3	28.5 • 4	28 • 5	27.5 • 6	27 • 7	26.5 • 8	26 • 9				
CARBON ROSE	Cable centered between timing dots	22.5-27"	80%†	TCL	27 • 1	26.5 • 2	26 • 3	25.5 • 4	25 • 5	24.5 • 6	24 • 7	23.5 • 8	23 • 9	22.5 • 10			

**REALM SR6 AND REALM SS ARE MARKED WITH ACTUAL DRAW LENGTHS

2019 CONVERGENCE TIMING AND POST SETTINGS CHART

TIMING MARK	DRAW INCHES	LET OFF	MOD LETTER	1 Draw Set	2 Draw Set	3 Draw Set	4 Draw Set	5 Draw Set	6 Draw Set	7 Draw Set	8 Draw Set	9 Draw Set	10 Draw Set	11 Draw Set	12 Draw Set	13 Draw Set	14 Draw Set	15 Draw Set	16 Draw Set	17 Draw Set	18 Draw Set	19 Draw Set
Cable centered between timing dots (A)	22-31"	80%	19L	31	30.5	30	29.5	29	28.5	28	27.5	27	26.5	26	25.5	25	24.5	24	23.5	23	22.5	22
Cable centered between timing dots (B)	21-30"	80%	19L	30	29.5	29	28.5	28	27.5	27	26.5	26	25.5	25	24.5	24	23.5	23	22.5	22	21.5	21

*80% EFFECTIVE

†65% TO 80% EFFECTIVE

90554 Highway 99 North • Eugene, Oregon 97402
 888-689-1289 toll free 541-284-4711 direct 541-284-4712 fax