



www.BowTechArchery.com

## 2004 BowTech Mod Chart

MODEL	BRACE	MOD USED	19	20	21	22	23	24	24.5	25	25.5	26	26.5	27	27.5	28	28.5	29	29.5	30	30.5	31	31.5	32
<b>BLACKKNIGHT</b>	5 3/4	DC								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>PATRIOT DUALY</b>	7 5/8	DC										6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1		
<b>PRO40 DUALY</b>	7	DC										6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1		
<b>PRO40 WHEELY</b>	7 1/4	W					8	7		6		5		4		3		2		1				
<b>PRO40</b>	8 1/4	F												6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1
<b>LIBERTY VFT</b>	7 1/2	F								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>JUSTICE VFT</b>	8	F								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>MIGHTYMITE VFT</b>	7 3/4	N								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>PATRIOT VFT</b>	7	N								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>EXTREME VFT</b>	6 5/8	I								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>SAMSON VFT</b>	6 5/8	I								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>TOMKAT</b>	9 1/8	I												6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1
<b>BLACKHAWK</b>	8	I								6	5.5	5	4.5	4	3.5	3	2.5	2	1.5	1				
<b>BLACKHAWK<sub>2</sub></b>	7 1/2	R		7	6	5	4	3		2		1												
<b>LADYHAWK</b>	7 1/2	R		7	6	5	4	3		2		1												
<b>RASCAL</b>	7 1/4	R	7	6	5	4	3	2		1														

W AND R MODS AVAILABLE IN 65% LETOFF = (WL AND RL)